

SPECIFICATION

TO ALL WHOM IT MAY CONCERN:

BE IT KNOWN THAT WE, Nobutaka Taniguchi, a citizen of Japan residing at Kawasaki, Japan and Hiroyoshi Tomita, a citizen of Japan residing at Kawasaki, Japan have invented certain new and useful improvements in

DELAY TIME ADJUSTING CIRCUIT COMPRISING FREQUENCY DIVIDERS
HAVING DIFFERENT FREQUENCY DIVISION RATES

of which the following is a specification : -

TITLE OF THE INVENTION

DELAY TIME ADJUSTING CIRCUIT COMPRISING
FREQUENCY DIVIDERS HAVING DIFFERENT FREQUENCY
DIVISION RATES

5

BACKGROUND OF THE INVENTION

1. Field of the Invention

The present invention generally relates to
a delay time adjusting circuit and, more
10 particularly, to a delay time adjusting circuit and
a delay time adjusting method which circuit and
method adjust a delay time of a signal transmitted
in a semiconductor integrated circuit.

2. Description of the Related Art

15 Conventionally, a semiconductor integrated
circuit, such as a DDR(Double Data Rate)-SDRAM,
which is required to operate at high speed and has a
DLL (Delay Locked Loop) circuit mounted thereon,
comprises a delay time adjusting circuit to adjust a
20 phase of a clock signal.

FIG.1 is a circuit diagram of the
conventional delay time adjusting circuit. As shown
in FIG.1, the conventional delay time adjusting
circuit comprises an input buffer 1, an output
25 buffer 5, frequency dividers 2 and 4, a DLL array 3,
a dummy circuit 6, a phase comparator 8 and a delay
adjuster 10.

In the conventional delay time adjusting
circuit, a clock signal is input into the input
30 buffer 1, which outputs a signal Cin. The frequency
divider 2 and the DLL array 3 are connected to the
input buffer 1. The frequency divider 4 and the
output buffer 5 are connected to an output terminal
of the DLL array 3. The frequency divider 2 outputs
35 a target clock signal tclk. The DLL array 3 outputs
a signal Cout. The output buffer 5 outputs a clock
signal delayed by the DLL array 3. The frequency

division rates of the frequency dividers 2 and 4 are equal.

The dummy circuit 6 is connected to the frequency divider 4 and outputs a delay clock signal dclk. The phase comparator 8 is connected to the frequency divider 2 and an output terminal of the dummy circuit 6, and feeds back a result signal 'out' to the delay adjuster 10, according to the supplied target clock signal tclk and the fed-back delay clock signal dclk. An output terminal of the delay adjuster 10 is connected to the DLL array 3. The delay adjuster 10 supplies a control signal CS to the DLL array 3.

FIG.2 is a circuit diagram of the DLL array 3 shown in FIG.1. As shown in FIG.2, the DLL array 3 comprises a switching unit 31 including a plurality of parallel-connected switches SW1 to SWn, and inverters INV1 to INVn respectively arranged to correspond to the switches SW1 to SWn. Switching of the switches SW1 to SWn included in the switching unit 31 is controlled by the controlling signal CS supplied by the delay adjuster 10. The signal Cin is delayed by a time td in each of the inverters INV1 to INVn.

In the above-mentioned delay time adjusting circuit, supposing that a delay time at the input buffer 1 is d1 and a delay time at the output buffer 5 is d2, a delay time at the dummy circuit 6 is (d1 + d2). Also, supposing that a delay time of the DLL array 3 is d3, the clock signal input into the input buffer 1 and output from the output buffer 5 is delayed by a time (d1 + d2 + d3).

Also, supposing that delay times at the frequency dividers 2 and 4 are d4, the clock signal input into the input buffer 1 and then input into the phase comparator 8 as the target clock signal

5 tclk is delayed by a time $(d1 + d4)$. In this case,
the clock signal input into the input buffer 1 and
consequently input into the phase comparator 8 as
the delay clock signal dclk is delayed by a time $(d1$
+ $d3 + d4 + (d1 + d2)$).

10 Accordingly, a difference in the delay
times between the target clock signal tclk and the
delay clock signal dclk is $(d1 + d2 + d3)$. This
difference equals the delay time $(d1 + d2 + d3)$ of
the clock signal input into the input buffer 1 and
output from the output buffer 5. Thereby, in order
to match phases of the clock signal input into the
input buffer 1 and the clock signal output from the
output buffer 5, the delay adjuster 10 adjusts the
15 delay time $d3$ of the DLL array 3 so that the
difference $(d1 + d2 + d3)$ in the delay times between
the target clock signal tclk and the delay clock
signal dclk equals a time corresponding to a number
 n (1, 2 or other natural numbers) of clocks of the
20 clock signal.

Here, a description will be given, with
reference to FIG.3 to FIG.7, of operations of the
above-mentioned delay time adjusting circuit. In a
case, shown in FIG.3, where a phase of a delay clock
25 signal dclk indicated by FIG.3-(b) is a time $F1$
behind a phase of the target clock signal tclk
indicated by FIG.3-(a), at so-called rise times $T1$,
 $T2$ and $T3$ when the target clock signal tclk rises
from a low level (L) to a high level (H), the delay
30 clock signal dclk is at a low level (L). In this
case, the phase comparator 8 supplies the delay
adjuster 10 with a result signal 'out' indicating a
judgment (decrease) that the phase of the delay
clock signal dclk is behind the phase of the target
35 clock signal tclk.

Thereby, the delay adjuster 10 supplies
the DLL array 3 with a control signal CS according

to the result signal 'out' so as to shorten a delay time in the DLL array 3 by the time F1. These operations match the phase of the delay clock signal dclk to the phase of the target clock signal tclk.

5 Likewise, the same or analogous operations apply to each of cases shown in FIG.4 to FIG.6, where a phase of a delay clock signal dclk is a time F2, F3 or F4 (each longer than the time F1) behind a phase of the target clock signal tclk.

10 In a case, shown in FIG.7, where a phase of a delay clock signal dclk indicated by FIG.7-(b) is a still longer time behind a phase of a target clock signal tclk indicated by FIG.7-(a), at the times T2 and T3, the delay clock signal dclk is at a
15 high level (H). In this case, the phase comparator 8 supplies the delay adjuster 10 with a result signal 'out' indicating a judgment (increase) that a first clock of the delay clock signal dclk is ahead of a second clock of the target clock signal tclk.

20 Thereby, the delay adjuster 10 supplies the DLL array 3 with a control signal CS according to the result signal 'out' so as to lengthen a delay time in the DLL array 3 by a time F5. In such a case shown in FIG.7, the phase of the delay clock
25 signal dclk is matched to the phase of the target clock signal tclk, based on the second clock of the target clock signal tclk.

FIG.8 is a circuit diagram of the phase comparator 8 shown in FIG.1. As shown in FIG.8, the
30 phase comparator 8 comprises NAND circuits 80 to 85. The target clock signal tclk is supplied to the NAND circuits 81 and 82. The delay clock signal dclk is supplied to the NAND circuit 83. The result signal 'out' is output from an output terminal of the NAND
35 circuit 84.

FIG.9 is a waveform diagram indicating an operation of the above-mentioned phase comparator 8

in a case where a first clock of a delay clock signal dclk is behind a first clock of a target clock signal tclk. FIG.9-(a) indicates the target clock signal tclk. FIG.9-(b) indicates the delay clock signal dclk. FIG.9-(c) indicates fluctuations of electric potential at an output node NA of the NAND circuit 81. FIG.9-(d) indicates fluctuations of electric potential at an output node NB of the NAND circuit 82. FIG.9-(e) indicates fluctuations of electric potential at an output node NC of the NAND circuit 80. FIG.9-(f) indicates fluctuations of electric potential at an output node ND of the NAND circuit 83. FIG.9-(g) indicates the result signal 'out'.

15 In the case shown in FIG.9, where the first clock of the delay clock signal dclk is behind the first clock of the target clock signal tclk, before a rise time TA of the target clock signal tclk, the NAND circuits 84 and 85 latch the result signal 'out' at a high level or a low level. Then, 20 at the rise time TA when the target clock signal tclk rises to a high level, the electric potential at the output node NB falls to a low level, and consequently, the result signal 'out' is fixed at the low level. Thereby, the phase comparator 8 25 supplies the delay adjuster 10 with the result signal 'out' at the low level. That is, the phase comparator 8 supplies the delay adjuster 10 with the result signal 'out' indicating a judgment (decrease) 30 that the first clock of the delay clock signal dclk is behind the first clock of the target clock signal tclk.

FIG.10 is a waveform diagram indicating an operation of the above-mentioned phase comparator 8 35 in a case where a first clock of a delay clock signal dclk is ahead of a first clock of a target clock signal tclk. FIG.10-(a) indicates the target

- clock signal tclk. FIG.10-(b) indicates the delay
clock signal dclk. FIG.10-(c) indicates
fluctuations of electric potential at the output
node NA of the NAND circuit 81. FIG.10-(d)
5 indicates fluctuations of electric potential at the
output node NB of the NAND circuit 82. FIG.10-(e)
indicates fluctuations of electric potential at the
output node NC of the NAND circuit 80. FIG.10-(f)
indicates fluctuations of electric potential at the
10 output node ND of the NAND circuit 83. FIG.10-(g)
indicates the result signal 'out'.

- In the case shown in FIG.10, where the
first clock of the delay clock signal dclk is ahead
of the first clock of the target clock signal tclk,
15 before the rise time T_A of the target clock signal
tclk, the NAND circuits 84 and 85 latch the result
signal 'out' at a high level or a low level. Then,
at the rise time T_A when the target clock signal
tclk rises to a high level, the electric potential
20 at the output node NA falls to a low level, and
consequently, the result signal 'out' is fixed at
the high level. Thereby, the phase comparator 8
supplies the delay adjuster 10 with the result
signal 'out' at the high level. That is, the phase
25 comparator 8 supplies the delay adjuster 10 with the
result signal 'out' indicating a judgment (increase)
that the first clock of the delay clock signal dclk
is ahead of the first clock of the target clock
signal tclk.

- 30 It should be noted that the above-
mentioned delay time of the DLL array 3 comprises a
variable component delay time that can be adjusted
by switching the switches SW1 to SWn included in the
switching unit 31, and a fixed component delay time
35 that is intrinsic to circuit properties of the DLL
array 3.

The conventional delay time adjusting

circuit operates as mentioned above. However, as a semiconductor integrated circuit is increasingly made to operate at high speed, and accordingly, a high-frequency signal is supplied to the input

5 buffer 1, the above-mentioned fixed component delay time occupies a larger portion of a required total delay time in a locking-on where the phases of the delay clock signal and the target clock signal are matched within a tolerance range.

10 As a countermeasure to this situation, conventionally, the frequency division rates of the frequency dividers 2 and 4 are raised so as to postpone in time a target used in matching the phases.

15 However, since dividing a frequency of the clock signal by n in the frequency divider 2 means that the target is postponed by a time corresponding to 2^n clocks, when n is increased so as to raise the above-mentioned frequency division rates, an
20 enormous number of the delay stages have to be provided in the DLL array 3 in consideration of a low-frequency band of the clock signal. This increases a scale of the delay time adjusting circuit.

25 SUMMARY OF THE INVENTION

It is a general object of the present invention to provide an improved and useful delay time adjusting method and a delay time adjusting
30 circuit in which method and circuit the above-mentioned problems are eliminated.

A more specific object of the present invention is to provide a delay time adjusting method which can adjust a delay time of a signal at
35 high speed and a delay time adjusting circuit which is reduced in scale but can realize the above-mentioned method.

In order to achieve the above-mentioned objects, there is provided according to one aspect of the present invention a delay time adjusting circuit which adjusts a delay time of an input signal so that a phase of the input signal and a phase of an output signal match each other, the circuit comprising:

first dividing means for dividing a frequency of the input signal by a first frequency division rate;

delaying means for delaying the input signal by a predetermined time;

second dividing means for dividing a frequency of the input signal delayed by the delaying means by a second frequency division rate;

comparing means for comparing a phase of a signal generated by the first dividing means and a phase of a signal generated by the second dividing means; and

adjusting means for adjusting the predetermined time according to a comparison result obtained by the comparing means.

According to the present invention, the first dividing means for dividing a frequency of the input signal can change the first frequency division rate so that a target in adjusting the delay time can be set at arbitrary intervals. Thus, decreasing the first frequency division rate can shorten a time required to adjust the delay time, and can reduce a circuit scale of the delaying means for delaying the input signal. Also, the second dividing means for dividing a frequency of the delayed input signal can change the second frequency division rate so as to arbitrarily determine how frequently the phases are compared. Thus, increasing the second frequency division rate so as to compare the phases less frequently can reduce an amount of electric power to

be consumed.

Additionally, in the present invention, the first frequency division rate may be reduced to 1 so as to make unnecessary a circuit element that realizes the first dividing means for dividing a frequency, reducing a circuit scale. Additionally, the comparing means for comparing phases may supply a signal indicating the comparison result to the adjusting means according to the signal generated by the second dividing means for dividing a frequency. According to the present invention, changing the second frequency division rate in the second dividing means for dividing a frequency can adjust how frequently the phases are compared.

In order to achieve the above-mentioned objects, there is provided according to another aspect of the present invention a delay time adjusting method which adjusts a delay time of an input signal so that a phase of the input signal and a phase of an output signal match each other, the method comprising:

a first step of comparing a phase of a signal generated by dividing, by a first frequency division rate, a frequency of the input signal, and a phase of a signal generated by dividing, by a second frequency division rate, a frequency of the input signal delayed by a predetermined time; and a second step of adjusting the predetermined time according to a comparison result obtained by the first step of comparing so that the phase of the signal generated by dividing by the first frequency division rate and the phase of the signal generated by dividing by the second frequency division rate match each other.

According to the present invention, the first frequency division rate can be changed so that a target in adjusting the delay time can be set at

arbitrary intervals. Thus, decreasing the first frequency division rate can shorten a time required to adjust the delay time. Also, the second frequency division rate can be changed so as to arbitrarily determine how frequently the phases are compared. Thus, increasing the second frequency division rate so as to compare the phases less frequently can reduce an amount of electric power to be consumed.

10 Additionally, in the present invention, the first frequency division rate may be reduced to 1 so as to use the input signal as a target in comparing the phases. This way, the first step of comparing phases can obtain the comparison result more quickly, enhancing a circuit operation speed. 15 Additionally, in the second step, the above-mentioned predetermined time may be adjusted at a frequency according to the signal generated by dividing a frequency of the delayed input signal by 20 the second frequency division rate. According to the present invention, changing the second frequency division rate can adjust how frequently the phases are compared.

Other objects, features and advantages of 25 the present invention will become more apparent from the following detailed description when read in conjunction with the accompanying drawings.

BRIEF DESCRIPTION OF THE DRAWINGS

30 FIG.1 is a circuit diagram of a conventional delay time adjusting circuit;

 FIG.2 is a circuit diagram of a DLL (Delay Locked Loop) array shown in FIG.1;

 FIG.3 is a first waveform diagram 35 indicating an operation of the conventional delay time adjusting circuit shown in FIG.1;

 FIG.4 is a second waveform diagram

indicating an operation of the conventional delay time adjusting circuit shown in FIG.1;

FIG.5 is a third waveform diagram indicating an operation of the conventional delay time adjusting circuit shown in FIG.1;

FIG.6 is a fourth waveform diagram indicating an operation of the conventional delay time adjusting circuit shown in FIG.1;

FIG.7 is a fifth waveform diagram indicating an operation of the conventional delay time adjusting circuit shown in FIG.1;

FIG.8 is a circuit diagram of a phase comparator shown in FIG.1;

FIG.9 is a waveform diagram indicating an operation of the phase comparator shown in FIG.8 in a case where a first clock of a delay clock signal is behind a first clock of a target clock signal;

FIG.10 is a waveform diagram indicating an operation of the phase comparator shown in FIG.8 in a case where a first clock of a delay clock signal is ahead of a first clock of a target clock signal;

FIG.11 is a circuit diagram of a delay time adjusting circuit according to an embodiment of the present invention;

FIG.12 is a circuit diagram of a delay time adjusting circuit according to another embodiment of the present invention;

FIG.13 is a first waveform diagram indicating an operation of the delay time adjusting circuit shown in FIG.12;

FIG.14 is a second waveform diagram indicating an operation of the delay time adjusting circuit shown in FIG.12;

FIG.15 is a third waveform diagram indicating an operation of the delay time adjusting circuit shown in FIG.12;

FIG.16 is a fourth waveform diagram

indicating an operation of the delay time adjusting circuit shown in FIG.12;

FIG.17 is a fifth waveform diagram indicating an operation of the delay time adjusting circuit shown in FIG.12;

FIG.18 is a circuit diagram of a phase comparator shown in FIG.12;

FIG.19 is a waveform diagram indicating an operation of the phase comparator shown in FIG.18 in a case where a first clock of a delay clock signal is behind a first clock of a target clock signal; and

FIG.20 is a waveform diagram indicating an operation of the phase comparator shown in FIG.18 in a case where a first clock of a delay clock signal is ahead of a first clock of a target clock signal.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

A description will now be given, with reference to the drawings, of embodiments according to the present invention. Elements in the drawings that are identical or equivalent are referenced by the same characters.

FIG.11 is a circuit diagram of a delay time adjusting circuit according to an embodiment of the present invention. As shown in FIG.11, the delay time adjusting circuit according to the present embodiment comprises the input buffer 1, the output buffer 5, a first frequency divider 11, a second frequency divider 12, the DLL array 3, the dummy circuit 6, a phase comparator 9 and the delay adjuster 10.

As described in detail hereinafter, the first frequency divider 11 may be considered to be an element that determines a target used in adjusting a phase of a signal. The second frequency divider 12 may be considered to be an element that

determines how frequently the phase of a signal has a chance to be adjusted. Therefore, when a frequency division rate of the second frequency divider 12 is increased so that the phase of a signal has a less frequent chance to be adjusted, only a smaller amount of electric current is consumed.

In the above-mentioned delay time adjusting circuit, a clock signal is input into the input buffer 1. The first frequency divider 11 and the DLL array 3 are connected to the input buffer 1. The second frequency divider 12 and the output buffer 5 are connected to the output terminal of the DLL array 3. The first frequency divider 11 outputs the target clock signal tclk. The above-mentioned delay time adjusting circuit is characterized in that frequency division rates are different between the first frequency divider 11 and the second frequency divider 12.

The dummy circuit 6 is connected to the second frequency divider 12 and outputs the delay clock signal dclk. The phase comparator 9 is connected to the first frequency divider 11 and the output terminal of the dummy circuit 6, and outputs the result signal 'out'. The delay adjuster 10 is connected to the phase comparator 9, and the output terminal of the delay adjuster 10 is connected to the DLL array 3. The delay adjuster 10 supplies the control signal CS to the DLL array 3.

The frequency division rate of the first frequency divider 11 may be set to 1. In this case, the first frequency divider 11 supplies an input signal to the phase comparator 9 as it is. Hence, the delay time adjusting circuit has a structure equivalent to a delay time adjusting circuit shown in FIG.12 without the first frequency divider 11, wherein an output signal from the input buffer 1 is

supplied directly to the phase comparator 9 as the target clock signal tclk. The delay time adjusting circuit shown in FIG.12 requires a smaller number of delay stages (the inverters INV1 to INVn) to be included in a DLL array 7 than that of a conventional technology, as mentioned hereinafter.

Next, a description will be given, with reference to FIG.13 to FIG.17, of operations of the above-mentioned delay time adjusting circuit shown in FIG.12. Here, a frequency division rate of the second frequency divider 12 shown in FIG.12 is set to four.

Accordingly, a delay clock signal dclk indicated by FIG.13-(b) has one fourth the frequency of that of a target clock signal tclk indicated by FIG.13-(a). In a case where a first clock of the delay clock signal dclk is a time F6 behind a first clock of the target clock signal tclk, at the rise times T1, T2 and T3 when the target clock signal tclk rises from a low level (L) to a high level (H), the delay clock signal dclk is at a low level (L). In this case, the phase comparator 9 supplies the delay adjuster 10 with a result signal 'out' indicating a judgment (decrease) that a phase of the delay clock signal dclk is behind a phase of the target clock signal tclk.

Thereby, the delay adjuster 10 supplies the DLL array 7 with a control signal CS according to the result signal 'out' so as to shorten a delay time in the DLL array 7 by the time F6. These operations match the phase of the delay clock signal dclk to the phase of the target clock signal tclk.

In a case, shown in FIG.14, where a first clock of a delay clock signal dclk indicated by FIG.14-(b) is a longer time behind a first clock of a target clock signal tclk indicated by FIG.14-(a), at a time T4, the delay clock signal dclk is at a

high level (H). In this case, the phase comparator 9 supplies the delay adjuster 10 with a result signal 'out' indicating a judgment (increase) that the first clock of the delay clock signal dclk is ahead of a second clock of the target clock signal tclk. Thereby, the delay adjuster 10 supplies the DLL array 7 with a control signal CS according to the result signal 'out' so as to lengthen a delay time in the DLL array 7 by a time F7. In such a case shown in FIG.14, the phase of the delay clock signal dclk is matched to the phase of the target clock signal tclk, based on the second clock of the target clock signal tclk.

In a case, shown in FIG.15, where a first clock of a delay clock signal dclk indicated by FIG.15-(b) is an even longer time behind a first clock of a target clock signal tclk indicated by FIG.15-(a), at the time T4 when the target clock signal tclk rises from a low level (L) to a high level (H), the delay clock signal dclk is at a low level (L). Accordingly, in this case, the phase comparator 9 supplies the delay adjuster 10 with a result signal 'out' indicating a judgment (decrease) that the first clock of the delay clock signal dclk is behind a second clock of the target clock signal tclk.

Thereby, the delay adjuster 10 supplies the DLL array 7 with a control signal CS according to the result signal 'out' so as to shorten a delay time in the DLL array 7 by a time F8. These operations match the phase of the delay clock signal dclk to the phase of the target clock signal tclk.

In a case, shown in FIG.16, where a phase of a delay clock signal dclk indicated by FIG.16-(b) is a still longer time behind a phase of a target clock signal tclk indicated by FIG.16-(a), at a time T5, the delay clock signal dclk is at a high level

(H). In this case, the phase comparator 9 supplies the delay adjuster 10 with a result signal 'out' indicating a judgment (increase) that a first clock of the delay clock signal dclk is ahead of a third clock of the target clock signal tclk.

Thereby, the delay adjuster 10 supplies the DLL array 7 with a control signal CS according to the result signal 'out' so as to lengthen a delay time in the DLL array 7 by a time F9. In such a case shown in FIG.16, the phase of the delay clock signal dclk is matched to the phase of the target clock signal tclk, based on the third clock of the target clock signal tclk.

In a case, shown in FIG.17, where a phase of a delay clock signal dclk indicated by FIG.17-(b) is a yet longer time behind a phase of a target clock signal tclk indicated by FIG.17-(a), at the time T5 when the target clock signal tclk rises from a low level (L) to a high level (H), the delay clock signal dclk is at a low level (L). Accordingly, in this case, the phase comparator 9 supplies the delay adjuster 10 with a result signal 'out' indicating a judgment (decrease) that a first clock of the delay clock signal dclk is behind a third clock of the target clock signal tclk.

Thereby, the delay adjuster 10 supplies the DLL array 7 with a control signal CS according to the result signal 'out' so as to shorten a delay time in the DLL array 7 by a time F10. These operations match the phase of the delay clock signal dclk to the phase of the target clock signal tclk.

FIG.18 is a circuit diagram of the phase comparator 9 shown in FIG.12. As shown in FIG.18, the phase comparator 9 comprises NAND circuits 90 to 95. The delay clock signal dclk is supplied to the NAND circuits 91 and 92. The target clock signal tclk is supplied to the NAND circuit 93. The result

signal 'out' is output from an output terminal of the NAND circuit 95. As described in detail hereinafter, the phase comparator 9 outputs the result signal 'out' indicating a judgment made according to a rise time of the delay clock signal dclk. Accordingly, when a frequency division rate of the second frequency divider 12 is increased so that a phase of a signal has a less frequent chance to be adjusted, only a smaller amount of electric current is consumed.

FIG.19 is a waveform diagram indicating an operation of the above-mentioned phase comparator 9 in a case where a first clock of a delay clock signal dclk is behind a first clock of a target clock signal tclk. FIG.19-(a) indicates the target clock signal tclk. FIG.19-(b) indicates the delay clock signal dclk. FIG.19-(c) indicates fluctuations of electric potential at an output node NA of the NAND circuit 91. FIG.19-(d) indicates fluctuations of electric potential at an output node NB of the NAND circuit 92. FIG.19-(e) indicates fluctuations of electric potential at an output node NC of the NAND circuit 90. FIG.19-(f) indicates fluctuations of electric potential at an output node ND of the NAND circuit 93. FIG.19-(g) indicates the result signal 'out'.

In the case shown in FIG.19, where the first clock of the delay clock signal dclk is behind the first clock of the target clock signal tclk, before a rise time TB of the delay clock signal dclk, the NAND circuits 94 and 95 latch the result signal 'out' at a high level or a low level. Then, when the delay clock signal dclk rises to a high level at the rise time TB, the electric potential at the output node NA falls to a low level, and consequently, the result signal 'out' is fixed at the low level. Thereby, the phase comparator 9

supplies the delay adjuster 10 with the result
signal 'out' at the low level. That is, the phase
comparator 9 supplies the delay adjuster 10 with the
result signal 'out' indicating a judgment (decrease)
5 that the first clock of the delay clock signal dclk
is behind the first clock of the target clock signal
tclk.

FIG.20 is a waveform diagram indicating an
operation of the above-mentioned phase comparator 9
10 in a case where a first clock of a delay clock
signal dclk is ahead of a first clock of a target
clock signal tclk. FIG.20-(a) indicates the target
clock signal tclk. FIG.20-(b) indicates the delay
clock signal dclk. FIG.20-(c) indicates
15 fluctuations of electric potential at the output
node NA of the NAND circuit 91. FIG.20-(d)
indicates fluctuations of electric potential at the
output node NB of the NAND circuit 92. FIG.20-(e)
indicates fluctuations of electric potential at the
20 output node NC of the NAND circuit 90. FIG.20-(f)
indicates fluctuations of electric potential at the
output node ND of the NAND circuit 93. FIG.20-(g)
indicates the result signal 'out'.

In the case shown in FIG.20, where the
25 first clock of the delay clock signal dclk is ahead
of the first clock of the target clock signal tclk,
before the rise time TB of the delay clock signal
dclk, the NAND circuits 94 and 95 latch the result
signal 'out' at a high level or a low level. Then,
30 when the delay clock signal dclk rises to a high
level at the rise time TB, the electric potential at
the output node NB falls to a low level, and
consequently, the result signal 'out' is fixed at
the high level. Thereby, the phase comparator 9
35 supplies the delay adjuster 10 with the result
signal 'out' at the high level. That is, the phase
comparator 9 supplies the delay adjuster 10 with the

result signal 'out' indicating a judgment (increase) that the first clock of the delay clock signal dclk is ahead of the first clock of the target clock signal tclk.

5 In the above-mentioned cases, a frequency division rate of the target clock signal tclk to an input clock signal supplied to the input buffer 1 is 1. Therefore, the target clock signal tclk has a higher frequency than that in a conventional delay
10 time adjusting circuit. Accordingly, clocks that the phase comparator 9 can use as a target in comparing the phases of the clock signals appear more frequently in a unit period of time. Thereby, since the nearest clock, whether behind or ahead, of
15 the target clock signal tclk to the first clock of the delay clock signal dclk is used as a target in matching the phases of the clock signals as mentioned above, a time by which to match the phases of the clock signals can be made smaller than in a
20 conventional delay time adjusting circuit.

Hence, the delay time adjusting circuit according to the present embodiment can shorten a length of a delay-time adjustment so as to quickly perform the adjustment of the delay time.
25 Additionally, in a low-frequency band of the input clock signal supplied to the input buffer 1, the DLL array 7 having a smaller number of the delay stages (the inverters INV1 to INVn) than that of a conventional technology is sufficient to adjust the
30 delay time. This reduces a scale of the delay time adjusting circuit.

The present invention is not limited to the specifically disclosed embodiments, and variations and modifications may be made without
35 departing from the scope of the present invention.

The present application is based on Japanese priority application No.2000-046226 filed

on February 23, 2000, the entire contents of which
are hereby incorporated by reference.

0
1
2
3
4
5
6
7
8
9
10
11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210
2211
2212
2213
2214
2215
2216
2217
2218
2219
2220
2221
2222
2223
2224
2225
2226
2227
2228
2